


SPRING CLAMP TERMINAL BLOCKS, SOLDERABLE, 3.50mm PITCH







- spring clamp terminal block, THR solderable, double solder
- centerline 3.50 mm, direction of connection 90°
- fittable without loss of poles
- color black
- · Tape & Reel packaging
- push-button

Technical data

c Nus V / A / AWG 150 / 10 / 28 - 16

^			
1.5 mm ² 130 V / 17.5 A	/ T60		
Overvoltage category	III	III	II
Pollution degree	3	2	2
Rated voltage	160 V	400 V	400 V
Rated test voltage	2.5 kV	2.5 kV	2.5 kV
Insulating material class	CTI 600		
Rated wiring solid wire	0.08 - 1.	.5 mm ²	
Rated wiring stranded wire	0.08 - 1.	.5 mm ²	
Rated wiring solid wire	AWG 28	- 16	
Rated wiring stranded wire	AWG 28	- 16	

IP 20

black

8.5 mm

Clearance and creepage distances 2 mm Solder pin dimension 2 x 0.4 x 0.8 mm Recommended pc board hole dia. ø 1.2 mm 3.45 mm


Solder pin length Protection category according to IEC 60529

Min. insul. strip length

SR213XXHBNC

Color

Dimensional drawing




02 03 04 05 06 07 08

09 10 11 12

SPRING CLAMP TERMINAL BLOCKS, **SOLDERABLE, 3.50mm PITCH**







- spring clamp terminal block, THR solderable, double solder pins
- centerline 3.50 mm, direction of connection 90°
- · fittable without loss of poles
- color black
- Tape & Reel packaging
- · finger push-button

Technical data

c Nus V/A/AWG 150/10/28-16

1.5 mm² 130 V / 17.5 A / T60 Overvoltage category III 111 П Pollution degree 2 Rated voltage 160 V 400 V 400 V Rated test voltage 2.5 kV 2.5 kV Insulating material class CTI 600


0.08 - 1.5 mm² Rated wiring solid wire 0.08 - 1.5 mm² Rated wiring stranded wire AWG 28 - 16 Rated wiring solid wire Rated wiring stranded wire AWG 28 - 16 Clearance and creepage distances 2 mm

Solder pin dimension 2 x 0.4 x 0.8 mm Recommended pc board hole dia. ø 1.2 mm Solder pin length 3.45 mm

Protection category according to IEC 60529

IP 20 8.5 mm Min. insul. strip length Color black

Dimensional drawing



SR213XXHBPC HBPC

	02	03	04	05	06	07	08
09	10	11	12				

Complete the part number by adding the pole size.